

## Supplementary information for the MP3SA-KP5 harness For the Technovision MP3SA player

The 5 pairs of wires on the MP3SA-KP5 harness are labelled 0, 1, 2, 3, and 4. These represent the row and column on the keypad port that the wires are attached to. These 5 pairs or wires should be mapped out in the CONFIG.TXT file as follows:

<u>Pair label</u>	<u>Key mapping in CONFIG.TXT</u>
0	key 00 **
1	key 11 **
2	key 22 **
3	key 33 **
4	key 44 **

Where \*\* will be the  
**KEY** function:

### Examples:

key 00 song1	will play song 1 when the pair of contacts, labelled 00, are contacted.
key 11 disc2	will play disc 2 when the pair of contacts, labelled 11, are contacted
key 22 play	will put the MP3SA into PLAY when the pair of contacts, labelled 22 are contacted.

### Other KEY functions:

pause	stop	play
next (track)*	prev (song)	disc+
disc-	songXX	discXX
replay (song)	track1	last (song)
ff	rew	vol+
vol-	max (vol)	min (vol)
mute	mute2 (toggle)	brup
brdn	brsel	brtoggle
repeat (cycle)	reset	

\*text within brackets are for descriptive purpose only.